

# Laserliner®

## AC-tiveFinder



Work safely on electrical lines –  
in handy pen format

Rev. 0211



- **Contactless detection** of live lines from 24 V AC to 1000 V AC
- **Locates electrical voltages** in cables, sockets, bulb sockets and fuses
- **Finds breaks** in wires and cables
- **CAT III - 1000 V** – can be used for measurements throughout building installations
- **Extremely high sensitivity** for tracing lines at great depths (Zoom)
- **Clearly visible LED** for signalling electrical voltages
- **Super-bright, integrated flashlight** with separate ON/OFF button
- **Compact design** with convenient clip, practical for shirt pockets and tool boxes
- Rugged, impact-resistant **quality enclosure**

### TECHNICAL DATA

<b>INDICATOR LED</b>
<b>VOLTAGE RANGE</b> 24 V AC ~ 1000 V AC Frequency 50 ... 60 Hz
<b>OVERVOLTAGE CATEGORY</b> CAT III – 1000 V (non-condensing) Pollution degree 2
<b>DIMENSIONS (W X H X D)</b> 158 x 21 x 25 mm
<b>BATTERY</b> 2 x 1.5 AAA (NEDA 24A/IEC LR 03)
<b>OPERATING TEMPERATURE</b> -10°C ... 50°C
<b>WEIGHT</b> 48 g



ZOOM function



Super-bright flashlight



**AC-tiveFinder**  
+ Batteries (2 x 1.5 AAA)

**Package size (W X H X D)**  
107 x 234 x 44 mm

ARTICLE	ARTICLE NO.	EAN CODE	PU
AC-tiveFinder	083.010A	4 021563 671144	5